



Kvaser LAPcan II

EAN: 73-30130-00115-2

The Kvaser LAPcan II is a two-channel CAN interface for the PC card (PCMCIA) bus. It is equipped with dual Philips SJA1000 CAN controllers, and has a high performance microprocessor and memory architecture, as well as enhanced ESD robustness.

Kvaser LAPcan II is a two-channel CAN interface for the PC card (PCMCIA) bus . It is equipped with dual Philips SJA1000 CAN controllers, and has a high performance microprocessor and memory architecture, as well as enhanced ESD robustness.

Major features



- Quick and easy plug-and-play installation
- The CAN drivers (DRVcans) are exchangeable; see below
- PC card (PCMCIA) type II, on-board C161 16-bit controller
- Ultrasonically welded card frame
- Supports both 11-bit (CAN 2.0A) and 29-bit (CAN 2.0B active) identifiers
- Driver support for major Operating Systems
- Physical layer depends on the DRVcan type
- Large on-board RAM buffer for CAN messages
- Supports "listen-only" mode for analyzing tools
-



The on-board firmware will auto-detect the type of DRVcan



TECHNICAL DATA - KVASER LAPCAN II

SOUND	No
INVENTORY	Call Us
ERROR FRAME GENERATION	Yes
CURRENT CONSUMPTION	N/A
CLOCK SYNC	No
WIDTH (MM)	85
OPERATING SYSTEM	Win XP, Linux, Win 7, Win Vista, Win 10, Win 8
CIRCUIT BOARD	No
PC INTERFACE	PCMCIA
PRODUCT GROUPS	
MINIMUM BITRATE (KBPS)	5
MSGRATE RX MAX	N/A
RUGGED	No
OPERATING TEMPERATURE RANGE (C)	+0 °C to +55 °C
CAN FD	No
GALVANIC ISOLATION	No
DATABASE DBC SUPPORT	No
MAXIMUM BITRATE (KBPS)	1000
MSGRATE TX MAX	N/A
API, LICENCED	None
WEIGHT (G)	50.0
EMBEDDED SCRIPT	No
HEIGHT (MM)	5
SILENT MODE	Yes
ERROR FRAME DETECTION	Yes
ON-BOARD TX BUFFER	N/A
STATUS	Obsolete

Kvaser
Aminogatan 25 A SE 431 53 Mölndal SWEDEN
Kvaser Europe AB
Telephone: +46 31 886344
Email: sales@kvaser.com
<https://www.kvaser.com/>



API, FREE	N/A
LENGTH (MM)	54
CERTIFICATIONS	CE
NETWORK CHANNEL(S)	1 x CAN HS
CONNECTOR	N/A
TIMESTAMP RESOLUTION (US)	8
ERROR COUNTERS READING	Yes
ON-BOARD RX BUFFER	N/A
CASING MATERIAL	Metal
IP CLASS	IP40
# OF CAN CHANNELS	2
ON-BOARD BUFFER	Yes

The information herein is subject to change without notice